












A22N/M22N/A30N

Accessories and Tools

Ordering Information

Accessories and Tools (Order Separately)

Item	Appearance	Classification	Model	Remarks			
Protective Cover		---	A22NZ-A-303	A protector designed to prevent incorrect operation. Cannot be used together with other accessories. (Rubber seal included.) For 22.3 and 25.5-mm panel holes diameter. Key-type selector switches cannot be used.			
Plastic Hole Plug		Round	A22NZ-A-401	Can be plugged into precut panel holes for future expansion. Applicable panel thickness: 0.8 to 3.0 mm For 22.3-mm panel hole diameter.			
Metal Hole Plug		Round	A22NZ-A-402	Can be plugged into precut panel holes for future expansion. Applicable panel thickness: 0.8 to 6.0 mm (Rubber seal included.) For 22.3-mm panel hole diameter.			
Lock Ring		Round	A22NZ-A-403	Used when a more secure lock is required to prevent rotation inside the Operation Unit. (Rubber seal included.) For 22.3-mm panel hole diameter. Can be used together with the A22NZ-A-50501 Lock Ring.			
Lock Ring		---	A22NZ-A-50501	Used when a more secure lock is required to prevent rotation of the Operation Unit. Can be used together with the A22NZ-A-403 Lock Ring. Can be used with the A22N Series and the A30N Series.			
Reinforcement Plate		---	A22NZ-A-C01	Used to reinforce Contact Blocks and Lighting Units. Refer to page 92 for mounting instructions.			
Key		---	A22NZ-K-01	Used with a key-type selector switch.			
Control Box		1 hole	A22NZ-A-B101 A22NZ-A-B201	For 22.3-mm panel hole diameter, A30N□ cannot be used. Two switches for screw terminal block type cannot be linked. The A22NZ-A-B01Y and The A22NZ-A-B2□ model cannot be used for a double-contact unit of the Push-In Plus terminal block type.			
		1 hole, yellow box	A22NZ-A-B101Y A22NZ-A-B01Y				
		2 holes	A22NZ-A-B102 A22NZ-A-B202				
		3 holes	A22NZ-A-B103 A22NZ-A-B203				
		Connector			Suitable Cable Diameter (mm)	7 to 9 dia. A22Z-3500-1 9 to 11 dia. A22Z-3500-2	Plastic connector used to extend a cable from the switch box. Refer to page 95 for details.
		Sealing Caps				For flat models	
	For projection models	A22Z-3600T					
	For full-guard models	A22Z-3600G					
Resin Attachment for 30 dia.		Round	A22Z-A30	Use when mounting to a panel with a 30-dia. hole. Refer to page 96 for details. Purchase and mount a separate Lock Ring when using an indicator.			