## Stainless Steel Sensing Surface Amplifier Proximity Sensor

# E2EC-M/-Q

CSM\_E2EC-M\_-Q\_DS\_E\_5\_2

CE



## Improved Durability with Stainless Steel Sensing Head

Models with improved spatter resistance ideal for welding also available.



E2EC-M E2EC-Q Sensing Surface has 10 times the strength against wear, compared to previous models.



E2EC-M E2EC-Q Sensing head is 18 mm in length. Ideal for use embedded in devices.



Fluoride coating

E2EC-Q
Prevents adherence
of weld spatter to
the Sensing Head.
(Improved
spatter-resistant
model)



Employs a fluoride cable (Improved spatter-resistant model)

E2EC-Q

For the most recent information on models that have been certified for safety standards, refer to your OMRON website.



Be sure to read Safety Precautions on page 5.

### Ordering Information

#### Sensors [Refer to Dimensions on page 6.]

Appearance		Consing distance	Output configuration	Model
		Sensing distance		Operation mode: NO
Shielded  When mounting to an iron surface	8 dia.	2 mm	DC 3-wire PNP	E2EC-MC2B1 2M
			DC 2-wire (polarity)	E2EC-MC2D1 2M
			DC 2-wire (no polarity) (3)-(4) pin arrangement	E2EC-QC2D1-M1GJ-T 0.3M

### **Accessories (Order Separately)**

Sensor I/O Connector (M12, Sockets on One Cable End)

Models with Pre-wired Connectors: A Connector is not provided with the Sensor. Be sure to order a Connector separately. [Refer to XS2.]

Appearance	Cable length	Sensor I/O Connector model	Applicable Proximity Sensors
Straight	2 m	XS2F-D421-DD0	
6	5 m	XS2F-D421-GD0	E2EC-QC2D1-M1GJ-T
L-shape	2 m	XS2F-D422-DD0	
	5 m	XS2F-D422-GD0	

Note: The Sensor I/O Connector models in the previous table are for standard cables. Be sure to use a heat-resistant cable (XS2F-D42 -- 80F) when using the Sensor in environments susceptible to spatter.